



**Build-up Unit - Supports Large and ENG/EPF lens adaptor**

## **AK-HBU500**

Build-up Unit - Supports Large and ENG/EPF lens adaptor

### **Key Features**

---

Camera can be mounted fast and smoothly

---

One cable solution

---

Power Output: DC12V/7.5A and DC12V/1.5A

---

3 User buttons

---

3 Cursor memories/button



## AK-HBU500

<https://ap.connect.panasonic.com/m/y/en/ak-hbu500>

<b>Power Supply</b>	12 V DC (when external power is supplied) 240 V AC 50 Hz/60 Hz (when AK-UCU500 is connected)
<b>Power Consumption</b>	70 W (when external power is supplied) 165 W (when AK-UCU500 is connected)
<b>Operating Temperature</b>	-10°C to 45°C (14°F to 113°F)
<b>Operating Humidity Range</b>	85% or less (relative humidity)
<b>Storage Temperature</b>	-20°C to 60°C (-4°F to 140°F)
<b>Weight</b>	Approx. 12.8 kg (28.22 lb) (unit only)
<b>Dimensions (W x H x D)</b>	300 mm x 417 mm x 510 mm (16-7/16 inches x 20-1/16 inches x 11-13/16 inches)
<b>Camera Number Display</b>	1 to 15 (depending on system settings)
<b>Lens I/F Connector</b>	36-pin x 1
<b>Camera I/F Connector</b>	20-pin x 1
<b>[DC In] Connector</b>	XLR x 1, 4-pin, 12 V DC
<b>[DC Out 12V 1.5A] Connector</b>	4-pin x 1
<b>[DC Out 12V 7.5A] Connector</b>	XLR x 1, 4-pin
<b>Note</b>	<p>*1: Depending on the setting, only one of them can be selected at one time.</p> <p>*2: The BB (black burst) signal and tri-level sync signal of the reference input are recognized automatically.</p> <p>*3: IP video cannot be transmitted when [CCU MODE] is set to [2160/23.98p], [2160/23.98PsF], [1080/23.98p], or [1080/23.98PsF].</p> <p>*4: Can be provided from CCU</p>