



Transmission Camera System to Be Configured at Low Cost

AK-UCU500

Single 2U rack-mounted camera control unit that provides a parallel UHD and HD/SD output over a distance of 2000m

Key Features

Provides a parallel UHD and HD/SD output HD output from camera (3G-SDI): 1080/59.94p, 50p, 59.94i, 50i, 29.97psF, 25psF, 23.98p over 59.94i, 720/59.94p, 50p UHD output from CCU: 2160/59.94p, 50p, 29.97p, 29.97psF, 25p, 25psF, 23.98p, 23.98psF SD output fr

Capable of optical fiber transmission of uncompressed video signals and camera power over a distance of 2000m

Variable Operation with Advanced Trunk functions

Supports IP streaming



AK-UCU500

<https://ap.connect.panasonic.com/sg/en/ak-ucu500>

| | |
|---|---|
| Camera Control Unit (CCU) -> General | 100 V - 120 V AC, 50 Hz/60 Hz |
| -> Power Supply | |
| Camera Control Unit (CCU) -> General | 500 W (Without camera connected: 70 W) |
| -> Power Consumption | |
| Camera Control Unit (CCU) -> General | 240 V AC (tolerance: 5%), 1.46 A, 50 Hz/60 Hz |
| -> Capacity for Supplying Power to a Camera | |
| Camera Control Unit (CCU) -> General | 0 °C to 40 °C (32 °F to 104 °F) |
| -> Operating Temperature | |
| Camera Control Unit (CCU) -> General | 10 % to 90 % (no condensation) |
| -> Humidity | |
| Camera Control Unit (CCU) -> General | Approx. 8.8 kg (19.4 lb) |
| -> Weight | |
| Camera Control Unit (CCU) -> General | W 424 mm x H 88 mm x D 401 mm (16-5/8 inches x 3-7/16 inches x 15-13/16 inches) |
| -> Dimensions | (excluding protrusions) |
| Camera Control Unit (CCU) -> Input/Output -> Video Output | 3G/HD/SD-SDI 7 lines (embedded audio is supported only for HD signals) HD/SD-SDI 1 line (shared with picture monitor output ^{*1} ; embedded audio is supported only for HD signals) Analog composite 2 lines (1 line shared with picture monitor output ^{*1}) HD-SDI 1 line (cannot be used in UHD/HS mode) |
| Camera Control Unit (CCU) -> Input/Output -> HD TRUNK output | |
| Camera Control Unit (CCU) -> Input/Output -> Return Input | 3G-HD/HD/SD-SDI 4 lines (RET1 input has active-through output) Analog composite 1 lines |
| Camera Control Unit (CCU) -> Input/Output -> Prompter Input | HD-SDI 1 line (with active-through output) Analog composite 2 lines (through output of 1 and input of 2 share the connector ^{*1}) It is not terminated when the unit is turned OFF. No through output |
| Camera Control Unit (CCU) -> Input/Output -> Reference Input | BB (black burst) / tri-level ^{*2} : 1 line (automatic termination, connect to upper connector; BB signal and tri-level ^{*2} signal automatically recognized, with loop-through output) |
| Camera Control Unit (CCU) -> Input/Output -> Microphone Output | 0 dBm/600 Ω, 2 lines (XLR, 3-pin, male) |
| Camera Control Unit (CCU) -> Input/Output -> Communication | Intercom input/output (ENG / PROD, 0 dBm, 600 Ω (4 W) / 1 V [p-p], 200 Ω (RTS), 4 W / RTS / CLRCOM): 2 lines ^{*1} PGM input (0 dBm/600 Ω): 2 lines ^{*1} Tally input (red, green, yellow): 1 input each |
| Camera Control Unit (CCU) -> Input/Output -> AUX | WFM control 6-bit (open collector output, terminal shared with camera microphone gain setting ^{*1}) Camera microphone gain setting input 5-bit (photo-coupler input ^{*1} , terminal shared with WFM control ^{*1}) Down-conversion system setting input 2-bit (photo-coupler input) |
| Camera Control Unit (CCU) -> Input/Output -> TRUNK | RS-422 / RS-232C 2 lines ^{*1} |
| Camera Control Unit (CCU) -> Input/Output -> ROP | RS-422 1 line, 16 V DC output (only one of this and FRONT/REAR ROP can be selected at one time via the menu or the [ROP FRONT/REAR] selection switch on the front panel) |
| Camera Control Unit (CCU) -> Input/Output -> MSU | RS-422 1 line, GPI for control |
| Camera Control Unit (CCU) -> Input/Output -> LAN TRUNK | LAN connection with camera side via an optical cable ^{*3} 1 line, 100BASE-T, 1000BASE-T |
| Camera Control Unit (CCU) -> Input/Output -> LAN | Personal computer connection for distribution via the Web ^{*3} 1 line, 10BASE-T, 100BASE-TX (use a crossover cable when connecting directly with a personal computer) |

Footnote Description

Depending on the setting, only one of them can be selected at one time.

The BB (black burst) signal and tri-level sync signal of the reference input are recognized automatically.

IP video cannot be transmitted when [CCU MODE] is set to [2160/23.98p], [2160/23.98PsF], [1080/23.98p], or [1080/23.98PsF].