



LCD Projectors PT-EZ770Z/EZ770ZL/EW730Z/EW730ZL/EX800Z/EX800ZL

3LCD - 6,500 lumens - WUXGA - 1Lamp - Exchangeable lens - Digital Link - Powered H/V Lens Shift

PT-EZ770Z/EZ770ZL

High brightness, low TCO and flexible installation LCD Projector Ideal for use in education and corporate environments

Key Features

LCD, 6,500 lumens, WUXGA

Daylight View Basic function ensures clear and vivid image quality in bright environments

Integrated DIGITAL LINK and Displayport connection

Eco filter enables up to 15,000 hours of air filter replacement cycle $\,$









https://ap.connect.panasonic.com/vn /vi/products/projectors/ptez770zez770zl

EZ770Z/EZ770ZL

PT-







Lamp replacement cycle -> ECO	4,000 hours [ECO 1]
Lamp replacement cycle -> NORMAL	
Lamp replacement cycle -> ECO	
Duimbton	4,500 hours [ECO 2]*2
Brightness Resolution	6,500 lm (lamp power: Auto/Normal, Dynamic mode, Standard lens)
Contrast Ratio (typ.)	1,920 x 1,200 pixels 5,000:1 (full on/full off, lamp power: Auto, iris: On)
Screen size (diagonal)	1.02-10.16 m (40-400 in),1.52-10.16 m (60-400 in) with the ET-ELW22,16:10 aspect ratio
Center-to-corner zone ratio	90%
Lens	PT-EZ770Z:Powered zoom (throw ratio 1.7-2.8:1), powered focus F 1.7-2.3, f 26.9-45.4
Lens	mm
	PT-EZ770ZL:Optional powered zoom/focus lenses and fixed-focus lens
Lens shift -> Vertical(from center of	
screen)	
	from center of screen (powered)
Lens shift -> Horizontal(from center of screen)	±10 % from center of screen (powered)
Keystone correction range	Vertical ±40°, horizontal ±30°
Installation	Ceiling/floor, front/rear
Terminals -> HDMI [™] IN	HDMI TM 19-pin x 1 (Deep Color, compatible with HDCP),
Terminals -> DVI-D IN	audio signal: Linear PCM (Sampling frequency: 48 kHz/44.1 kHz/32 kHz) DVI-D 24-pin x 1 (DVI 1.0 compliant, compatible with HDCP,
	compatible with single link only)
Terminals -> DisplayPort [™] IN	DP-20P x 1 (DisplayPort 1.1, compatible with HDCP),
	audio signal: Linear PCM (Sampling frequency: 48 kHz/44.1 kHz/32 kHz)
Terminals -> COMPUTER IN (RGB IN)	b-sub tib 13-piii (tethale) x 1 (kdb/1+B+R/1-CBCR x 1)
Terminals -> COMPUTER OUT (D-SUB	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs)
Terminals -> COMPUTER OUT(D-SUB 15pin)	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs)
Terminals -> COMPUTER OUT(D-SUB 15pin) Terminals -> VIDEO IN	
Terminals -> COMPUTER OUT(D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video)
Terminals -> COMPUTER OUT(D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video)
Terminals -> COMPUTER OUT(D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack)	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2)
Terminals -> COMPUTER OUT(D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable)
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant)
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> REMOTE 1 OUT	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> REMOTE 1 OUT	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible)
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> REMOTE 1 OUT Terminals -> DIGITAL LINK IN / LAN Power supply	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible)
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> REMOTE 1 OUT Terminals -> DIGITAL LINK IN / LAN Power supply	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible)
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> REMOTE 1 OUT Terminals -> DIGITAL LINK IN / LAN Power supply	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible)
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> REMOTE 1 OUT Terminals -> DIGITAL LINK IN / LAN Power supply	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible) 100-240 V AC, 50/60 Hz 590 W (0.3 W when
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> REMOTE 1 OUT Terminals -> DIGITAL LINK IN / LAN Power supply	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible) 100-240 V AC, 50/60 Hz 590 W (0.3 W when
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> REMOTE 1 OUT Terminals -> DIGITAL LINK IN / LAN Power supply	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible) 100-240 V AC, 50/60 Hz 590 W (0.3 W when STANDBY MODE set to ECO*1,
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> DIGITAL LINK IN / LAN Power supply	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible) 100-240 V AC, 50/60 Hz 590 W (0.3 W when STANDBY MODE set to ECO*1, 10 W when
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> DIGITAL LINK IN / LAN Power supply	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible) 100-240 V AC, 50/60 Hz 590 W (0.3 W when STANDBY MODE set to ECO*1, 10 W when
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> DIGITAL LINK IN / LAN Power supply	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible) 100-240 V AC, 50/60 Hz 590 W (0.3 W when STANDBY MODE set to ECO*1, 10 W when
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> DIGITAL LINK IN / LAN Power supply	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible) 100-240 V AC, 50/60 Hz 590 W (0.3 W when STANDBY MODE set to ECO*1, 10 W when STANDBY MODE set to NORMAL (37 W when STANDBY MODE
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> DIGITAL LINK IN / LAN Power supply Maximum power consumption	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible) 100-240 V AC, 50/60 Hz 590 W (0.3 W when STANDBY MODE set to ECO*1, 10 W when STANDBY MODE set to NORMAL (37 W when STANDBY MODE of AUDIO SETTING set to ON))
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> REMOTE 1 OUT Terminals -> DIGITAL LINK IN / LAN Power supply Maximum power consumption	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible) 100-240 V AC, 50/60 Hz 590 W (0.3 W when STANDBY MODE set to ECO*1, 10 W when STANDBY MODE set to NORMAL (37 W when STANDBY MODE
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> DIGITAL LINK IN / LAN Power supply Maximum power consumption Standby power consumption -> Normal Standby power consumption -> ECO	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible) 100-240 V AC, 50/60 Hz 590 W (0.3 W when STANDBY MODE set to ECO*1, 10 W when STANDBY MODE set to NORMAL (37 W when STANDBY MODE of AUDIO SETTING set to ON)) 10W
Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> DIGITAL LINK IN / LAN Power supply Maximum power consumption Standby power consumption -> Normal Standby power consumption -> ECO	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible) 100-240 V AC, 50/60 Hz 590 W (0.3 W when STANDBY MODE set to ECO*1, 10 W when STANDBY MODE set to NORMAL (37 W when STANDBY MODE of AUDIO SETTING set to ON))
Terminals -> COMPUTER IN (RGB IN) Terminals -> COMPUTER OUT (D-SUB 15pin) Terminals -> VIDEO IN Terminals -> AUDIO IN(M3 Stereo Mini Jack) Terminals -> AUDIO OUT(M3 Stereo Mini Jack) Terminals -> SERIAL IN Terminals -> REMOTE 1 IN Terminals -> REMOTE 1 OUT Terminals -> DIGITAL LINK IN / LAN Power supply Maximum power consumption Standby power consumption -> Normal Standby power consumption -> ECO Power consumption	D-sub HD 15-pin (female) x 1 (RGB x 1) (not compatible with all inputs) Pin jack x 1 (composite video) Pin jack x 2 (L/R x 1), M3 x 2 (L-R x 2) M3 x 1 (L-R x 1) for output (variable) D-sub 9-pin (female) x 1 for external control (RS-232C compliant) M3 x 1 for wired remote control D-sub 9-pin (female) x 1 for external control (parallel) RJ-45 x 1 (for network and DIGITAL LINK (video/audio/network/serial control) connection 100Base-TX, compliant with PJLink TM , HDCP compatible, Deep Color compatible) 100-240 V AC, 50/60 Hz 590 W (0.3 W when STANDBY MODE set to ECO*1, 10 W when STANDBY MODE set to NORMAL (37 W when STANDBY MODE of AUDIO SETTING set to ON)) 10W

set to NORMAL (37 W when STANDBY MODE of AUDIO SETTING set to ON))

Built-in speaker	3.7 cm round shape x 1, output power 10.0 W (monaural)
Cabinet materials	Molded plastic (PC + ABS)
Filter	Included
Estimated filter maintenance cycle	15,000 hours
Operation noise -> Normal	37 dB [NORMAL]
Operation noise -> Eco	31 dB [ECO1]
	29 dB [ECO2]
Dimensions (W x H x D)	PT-EZ770Z: 530 x 177*8 x 445 mm (20-7/8 x 6-31/32*8 x 17-1/2 in) (with supplied lens
	PT-EZ770ZL: 530 x 177*8 x 385 mm (20-7/8 x 6-31/32*8 x 15-5/32 in) (without lens)
Dimensions -> Width (including protruding parts)	530 mm (20-7/8")
• • • • • • • • • • • • • • • • • • • •	477 (C. 24/221)
Dimensions -> Height (including protruding parts)	177 mm (6-31/32")
Dimensions -> Depth (not including protruding parts)	PT-EZ770ZL:385 mm (15-5/32")
Dimensions -> Depth (including lens)	PT-EZ770Z:445 mm (17-1/2")
Weight	PT-EZ770Z:Approx. 10.6 kg (23.4 lbs) (with supplied lens)
	PT-EZ770ZL:Approx. 9.8 kg (21.6 lbs) (without lens)
Operating environment -> Operating	0-45 °C (32-113 °F)
temperature	
Operating Environment -> Operating	10-80 % (no condensation)
humidity (No condensation)	
Footnote Description	*The PT-EZ770ZL/EW730ZL/EX800ZL delivers the same performance as the PT-EZ770Z/EW730Z/EX800, but comes without a lens.

- When the STANDBY MODE is set to ECO, network functions such as power on over the LAN will not operate. Also, only certain commands can be received for external control using the serial terminal.
- 2. This is the maximum value when the lamp is turned on for 2 hours and off for 0.25 hours. If the lamp is turned on more times or kept on for a long time, the lamp replacement cycle will shorten. The usage environment affects the duration of the lamp.
- Measurement, measuring conditions, and method of notation all comply with ISO 21118 international standards. Value is the average of all products when shipped.
- Measurement, measuring conditions, and method of notation all comply with American National Standards Institute standards. Value is the average of all products when shipped.
- 5. Input signals that exceed the native resolution will be converted to the native
- 6. The axis shift function cannot be used with the ET-ELW21.
- 7. With the supplied lens. Value differs when the correction for both directions is operated.
- 8. The usage environment affects the duration of the filter.
- 9. With legs at shortest position.
- 10. Average value. May differ depending on models.
- 11. The operating temperature range is 0 °C to 40 °C (32 °F to 104 °F) when used at altitudes between from 1,400 m to 2,700 m (4,593 ft to 8,858 ft) above sea level. Also, if the ambient temperature exceeds 40 °C (104 °F) (35 °C (95 °F) at high altitude), the LAMP POWER may be automatically switch to Eco 2 to in oeder to protect the projector.