



**Transmission Camera System to Be Configured at  
Low Cost**

## AK-UCU500

Single 2U rack-mounted camera control unit that provides a parallel  
UHD and HD/SD output over a distance of 2000m

### Key Features

Provides a parallel UHD and HD/SD output HD output from camera (3G-SDI): 1080/59.94p, 50p, 59.94i, 50i, 29.97psF, 25psF, 23.98p over 59.94i, 720/59.94p, 50p UHD output from CCU: 2160/59.94p, 50p, 29.97p, 29.97psF, 25p, 25psF, 23.98p, 23.98psF SD output fr

Capable of optical fiber transmission of uncompressed video signals and camera power over a distance of 2000m

Variable Operation with Advanced Trunk functions

Supports IP streaming



## AK-UCU500

<https://ap.connect.panasonic.com/vn/vi/ak-ucu500>

<b>Camera Control Unit (CCU) -&gt; General</b>	100 V - 120 V AC, 50 Hz/60 Hz
<b>-&gt; Power Supply</b>	
<b>Camera Control Unit (CCU) -&gt; General</b>	500 W (Without camera connected: 70 W)
<b>-&gt; Power Consumption</b>	
<b>Camera Control Unit (CCU) -&gt; General</b>	240 V AC (tolerance: 5%), 1.46 A, 50 Hz/60 Hz
<b>-&gt; Capacity for Supplying Power to a Camera</b>	
<b>Camera Control Unit (CCU) -&gt; General</b>	0 °C to 40 °C (32 °F to 104 °F)
<b>-&gt; Operating Temperature</b>	
<b>Camera Control Unit (CCU) -&gt; General</b>	10 % to 90 % (no condensation)
<b>-&gt; Humidity</b>	
<b>Camera Control Unit (CCU) -&gt; General</b>	Approx. 8.8 kg (19.4 lb)
<b>-&gt; Weight</b>	
<b>Camera Control Unit (CCU) -&gt; General</b>	W 424 mm x H 88 mm x D 401 mm (16-5/8 inches x 3-7/16 inches x 15-13/16 inches)
<b>-&gt; Dimensions</b>	(excluding protrusions)
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; Video Output</b>	3G/HD/SD-SDI 7 lines (embedded audio is supported only for HD signals) HD/SD-SDI 1 line (shared with picture monitor output <sup>*1</sup> ; embedded audio is supported only for HD signals) Analog composite 2 lines (1 line shared with picture monitor output <sup>*1</sup> ) HD-SDI 1 line (cannot be used in UHD/HS mode)
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; HD TRUNK output</b>	
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; Return Input</b>	3G-HD/HD/SD-SDI 4 lines (RET1 input has active-through output) Analog composite 1 lines
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; Prompter Input</b>	HD-SDI 1 line (with active-through output) Analog composite 2 lines (through output of 1 and input of 2 share the connector <sup>*1</sup> ) It is not terminated when the unit is turned OFF. No through output
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; Reference Input</b>	BB (black burst) / tri-level <sup>*2</sup> : 1 line (automatic termination, connect to upper connector; BB signal and tri-level <sup>*2</sup> signal automatically recognized, with loop-through output)
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; Microphone Output</b>	0 dBm/600 Ω, 2 lines (XLR, 3-pin, male)
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; Communication</b>	Intercom input/output (ENG / PROD, 0 dBm, 600 Ω (4 W) / 1 V [p-p], 200 Ω (RTS), 4 W / RTS / CLRCOM); 2 lines <sup>*1</sup> PGM input (0 dBm/600 Ω); 2 lines <sup>*1</sup> Tally input (red, green, yellow); 1 input each
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; AUX</b>	WFM control 6-bit (open collector output, terminal shared with camera microphone gain setting <sup>*1</sup> ) Camera microphone gain setting input 5-bit (photo-coupler input <sup>*1</sup> , terminal shared with WFM control <sup>*1</sup> ) Down-conversion system setting input 2-bit (photo-coupler input)
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; TRUNK</b>	RS-422 / RS-232C 2 lines <sup>*1</sup>
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; ROP</b>	RS-422 1 line, 16 V DC output (only one of this and FRONT/REAR ROP can be selected at one time via the menu or the [ROP FRONT/REAR] selection switch on the front panel)
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; MSU</b>	RS-422 1 line, GPI for control
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; LAN TRUNK</b>	LAN connection with camera side via an optical cable <sup>*3</sup> 1 line, 100BASE-T, 1000BASE-T
<b>Camera Control Unit (CCU) -&gt; Input/Output -&gt; LAN</b>	Personal computer connection for distribution via the Web <sup>*3</sup> 1 line, 10BASE-T, 100BASE-TX (use a crossover cable when connecting directly with a personal computer)
<b>Footnote Description</b>	1. Depending on the setting, only one of them can be selected at one time. 2. The BB (black burst) signal and tri-level sync signal of the reference input are recognized automatically. 3. IP video cannot be transmitted when [CCU MODE] is set to [2160/23.98p], [2160/23.98PsF], [1080/23.98p], or [1080/23.98PsF].