



**Ultra-short-throw lens, compatible with all Panasonic's 3-chip DLP™ projectors, enables large-screen projection from a short distance**

## **ET-D75LE95**

0.39:1 throw distance (WUXGA) Ultra Short-Throw Lens for 3-Chip DLP Projectors

### **Key Features**

---

200-inch diagonal image can be produced from a distance of only about 1.5 m (5.0 ft) away from the screen

---

Lenses can be used in both vertical and horizontal edge blending

---

Throw ratio: 0.39:1 (for 4K+) / 0.36:1 (for the WUXGA & full HD resolution) / 0.39:1 (for the SXGA+ resolution) / 0.40:1 (for the WXGA resolution)

ET-D75LE95

<https://ap.connect.panasonic.com/id/en/products/projectors/et-d75le95>

<b>F-number</b>	2.5
<b>Focal length (f)</b>	7.5 mm
<b>Throw ratio -&gt; WUXGA</b>	Approx. 0.36:1
<b>Throw ratio -&gt; Full HD</b>	Approx. 0.36:1
<b>Throw ratio -&gt; SXGA+</b>	Approx. 0.39:1
<b>Throw ratio -&gt; WXGA</b>	Approx. 0.40:1
<b>Lens-shift -&gt; Vertical</b>	PT-RQ32K/RQ22K/RQ13K : up: 10%, down: 5% RT-RZ31K/RZ21K/RZ12K/DZ21K/DZ21K2/DZ13K/DZ10K : up: 5%, down: 7% PT-DZ16K/DZ16K2 : up: 13%, down: 8% RT-RS30K/RS11K/DS20K/DS20K2/DS12K : up: 7%, down: 7% PT-DW17K/DW17K2/DW11K : up: 18%, down: 0%
<b>Lens-shift -&gt; Horizontal</b>	PT-RQ32K/RQ22K/RQ13K : left: 21%, right: 21% RT-RZ31K/RZ21K/RZ12K/DZ21K/DZ21K2/DZ13K/DZ10K : left: 12%, right: 12% PT-DZ16K/DZ16K2 : left: 19%, right: 19% RT-RS30K/RS11K/DS20K/DS20K2/DS12K : left: 8%, right: 8% PT-DW17K/DW17K2/DW11K : left: 13%, right: 27%
<b>Dimensions -&gt; (W)</b>	ø154 mm (ø 6 1/16")
<b>Dimensions -&gt; (H)</b>	ø154 mm (ø 6 1/16")
<b>Dimensions -&gt; (D)</b>	463.5 mm (18 1/4")
<b>Weight</b>	Approx. 5.7 kg (12.6 lbs)
<b>Applicable projectors</b>	PT-RQ35K/RZ34K

PT-RQ32K

PT-RQ25K/RZ24K/RQ18K/RZ17K

PT-RQ22K

PT-RQ13K

PT-RZ31K/RS30K

PT-RZ21K/RS20K

PT-RZ16K

PT-RZ12K/RS11K

PT-DZ21K/DZ21K2/DS20K/DS20K2/DW17K/DW17K2/DZ16K/DZ16K2

PT-DZ13K/DS12K/DW11K/DZ10K/DZ8700/DZ110K/DS8500/DS1100K/DW8300/DW90K

**Footnote Description**

Note: Due to lens characteristics, some screen types may be subject to focusing problems or strong hot spots where large differences in brightness occur between the hot spots and surrounding areas. If this should occur, please ask a qualified technician or your dealer for solutions.